


# LC5

## High Power Resonant Capacitors



### FEATURES

High AC Voltage - High Current

### APPLICATIONS

Induction Heating - Tank Circuits


KVAR	500
CAPACITANCE TOLERANCE	+/-10%
MAXIMUM CORE TEMPERATURE	+85°C
SURFACE TEMPERATURE	+45°C (Above 45°C the KVAR rating must be de-rated by 2.25%/°C)
CONSTRUCTION	Self-healing
SELF INDUCTANCE	< 3 nH
DIELECTRIC	Polypropylene
FLAME RETARDANT	UL94V0

### Standard Part Listing



Capacitance (µF)	VAC	IC PART number	Maximum RMS current (A)	MAX power kvar	Frequency range (kHz)	ESR (mΩ) 100kHz, +25°C	Dimensions (mm)			Terminal Style
							B	H	L	
1.2	1100	<a href="#">125LC5112K5PM8</a>	600	500	55-96	1.5	54	100	100	5PM8
1.4	1100	<a href="#">145LC5112K5PM8</a>	600	500	46-83	1.2	54	100	100	5PM8
3.0	750	<a href="#">305LC5750K5PM8</a>	800	500	47-68	1.1	54	100	100	5PM8
3.3	750	<a href="#">335LC5750K5PM8</a>	800	500	43-62	1.0	54	100	100	5PM8
4.0	900	<a href="#">405LC5900K5PM8</a>	700	500	25-39	0.9	54	100	100	5PM8
5.6	700	<a href="#">565LC5700K5PM8</a>	1000	500	29-57	0.9	54	100	100	5PM8
6.3	700	<a href="#">635LC5700K5PM8</a>	1000	500	26-51	0.8	54	100	100	5PM8
8.5	700	<a href="#">855LC5700K5PM8</a>	1000	500	19-38	0.7	54	100	100	5PM8
10	700	<a href="#">106LC5700K5PM8</a>	1000	500	16-32	0.6	54	100	100	5PM8
21	500	<a href="#">216LC5500K5PM8</a>	1000	500	15	0.4	54	100	100	5PM8
27	550	<a href="#">276LC5550K5PM8</a>	1000	500	10-12	0.3	54	100	100	5PM8
33	500	<a href="#">336LC5500K5PM8</a>	1000	500	10	0.3	54	100	100	5PM8
37	500	<a href="#">376LC5500K5PM8</a>	1000	500	9	0.2	54	100	100	5PM8

# LC5

## High Power Resonant Capacitors




LEAD STYLE:5PM8



L	H	B	H2	L2
100 $\pm$ 1.0	100 $\pm$ 1.0	54 $\pm$ 0.5	78 $\pm$ 0.5	78 $\pm$ 0.5
Mounting Holes: M8 Tap				
Tightening torque: 20Nm MAX				







# LC5

## High Power Resonant Capacitors




### Frequency Derating

— Voltage — Current — Power









# LC5

## High Power Resonant Capacitors




### Frequency Derating

—●— Voltage    —■— Current    —▲— Power




# LC5

## High Power Resonant Capacitors



### Frequency Derating



—●— Voltage    —■— Current    —▲— Power